

Item	FET	Type	Specification
1	BUZ 90	N-Channel	600v, 4.5A, 70W, 1.6ohm
2	BUZ 90A	N-Channel	600V, 4A, 70W, 2ohm
3	BUZ 91	N-Channel	600V, 8.5A, 150W, 0.8ohm
4	BUZ 91A	N-Channel	600V, 8A, 150W, 0.8ohm
5	BUZ 92	N-Channel	600V, 3.3A, 80W, 3ohm
6	BUZ 93	N-Channel	600V, 3.6A, 80W, 2.5ohm
7	BUZ 94	N-Channel	600V, 7.8A, 125W, 0.9ohm
8	IRF 510	N-Channel	100V, 5.6A, 43W, 0.54ohm
9	IRF 520	N-Channel	100V, 9.2A, 60W, 0.27ohm
10	IRF 530	N-Channel	100V, 14A, 88W, 0.16ohm
11	IRF 540	N-Channel	100V, 28A, 150W, 77 miliohm
12	IRF 610	N-Channel	200V, 3.3A, 26W, 1.5ohm
13	IRF 620	N-Channel	200V, 5.2A, 50W, 1.2ohm
14	IRF 630	N-Channel	200V, 9A, 74W, 0.4ohm
15	IRF 634	N-Channel	250V, 8.1A, 74W, 0.45ohm
16	IRF 640	N-Channel	200V, 18A, 125W, 0.18ohm
17	IRF 710	N-Channel	400V, 2A, 36W, 3.6ohm
18	IRF 720	N-Channel	400V, 3.3A, 50W, 1.8ohm
19	IRF 730	N-Channel	400V, 5.5A, 74W, 1ohm
20	IRF 740	N-Channel	400V, 10A, 125W, 0.55ohm
21	IRF 820	N-Channel	500V, 2.5A, 50W, 3ohm
22	IRF 830	N-Channel	500V, 4.5A, 74W, 4ohm
23	IRF 840	N-Channel	500V, 8A, 125W, 0.85ohm
24	IRF 841	N-Channel	450V, 8A, 125W, 0.85ohm
25	IRF 842	N-Channel	500V, 7A, 125W, 1.1ohm
26	IRF 843	N-Channel	450V, 7A, 125W, 1.1ohm
27	IRF 9610	P-Channel	200V, 1.8A, 20W, 3ohm
28	IRF 9620	P-Channel	200V, 3.5A, 40W, 1.5ohm
29	IRF 9630	P-Channel	200V, 6.5A, 74W, 0.8ohm
30	IRF 9640	P-Channel	200V, 11A, 125W, 0.5ohm
31	IRFI 510G	N-Channel	100V, 4.5A, 27W, 0.54ohm
32	IRFI 520G	N-Channel	100V, 7.2A, 37W, 0.27ohm
33	IRFI 530G	N-Channel	100V, 9.7A, 42W, 0.16ohm
34	IRFI 540G	N-Channel	100V, 17A, 48W, 77miliohm
35	IRFI 620G	N-Channel	200V, 4.1A, 30W, 0.8ohm

43	IRFI 830G	N-Channel	500V, 3.1A, 35W, 1.5ohm
44	IRFI 840G	N-Channel	500V, 4.6A, 40W, 0.85ohm
45	IRFI 9620G	P-Channel	200V, 2A, 30W, 1.5ohm
46	IRFI 9630G	P-Channel	200V, 4.3A, 30W, 0.8ohm
47	IRFI 9640G	P-Channel	200V, 6.1A, 40W, 0.5ohm
48	IRFS 520	N-Channel	100V, 7A, 30W, 0.27ohm
49	IRFS 530	N-Channel	100V, 9A, 35W, 0.16ohm
50	IRFS 540	N-Channel	100V, 15A, 40W, 77miliohm
51	IRFS 620	N-Channel	200V, 4A, 30W, 0.8ohm
52	IRFS 630	N-Channel	200V, 6.1A, 35W, 0.4ohm
53	IRFS 640	N-Channel	200V, 10.2A, 40W, 0.18ohm
54	IRFS 634	N-Channel	250V, 5.5A, 35W, 0.45ohm
55	IRFS 720	N-Channel	400V, 2.5A, 30W, 1.8ohm
56	IRFS 730	N-Channel	400V, 3.5A, 35W, 1ohm
57	IRFS 740	N-Channel	400V, 3.5A, 40W, 0.55ohm
58	IRFS 820	N-Channel	500V, 2A, 30W, 3ohm
59	IRFS 830	N-Channel	500V, 3A, 35W, 1.5ohm
60	IRFS 840	N-Channel	500V, 4.5A, 40W, 0.85ohm
61	IRFS 9620	P-Channel	200V, 3A, 30W, 1.5ohm
62	IRFS 9630	P-Channel	200V, 4.4A, 35W, 0.8ohm
63	IRFS 9640	P-Channel	200V, 6.2A, 40W, 0.5ohm
64	MTP6N10	N-Channel	100V, 6A, 50W
65	MTP6N55	N-Channel	550V, 6A, 125W
66	MTP6N60	N-Channel	600V, 6A, 125W
67	MTP7N20	N-Channel	200V, 7A, 75W
68	MTP8N80	N-Channel	80V, 8A, 75W
69	MTP8N10	N-Channel	100V, 8A, 75W
70	MTP8N12	N-Channel	120V, 8A, 75W
71	MTP8N13	N-Channel	130V, 8A, 75W
72	MTP8N14	N-Channel	140V, 8A, 75W
73	MTP8N15	N-Channel	150V, 8A, 75W
74	MTP8N18	N-Channel	180V, 8A, 75W
75	MTP8N19	N-Channel	190V, 8A, 75W
76	MTP8N20	N-Channel	200V, 8A, 75W
77	MTP8N45	N-Channel	450V, 8A, 125W
78	MTP8N46	N-Channel	460V, 8A, 125W

86	2SK525	N-Channel	150V, 10A, 40W, 0.28ohm
87	2SK526	N-Channel	250V, 10A, 40W, 0.6ohm
88	2SK527	N-Channel	60V, 10A, 40W, 0.14ohm
89	2SK555	N-Channel	500V, 7A, 60W, 0.85ohm
90	2SK556	N-Channel	450V, 12A, 100W, 0.55ohm
91	2SK557	N-Channel	500V, 12A, 100W, 0.55ohm
92	2SK727	N-Channel	850V, 5A, 125W
93	2SK791	N-Channel	850V, 3A, 100W, 4.5ohm
94	2SK792	N-Channel	900V, 3A, 100W, 4.5ohm
95	2Sk793	N-Channel	850V, 5A, 150W, 2.5ohm
96	2SK794	N-Channel	900V, 5A, 150W, 2.5ohm
97	2SK1038	N-Channel	400V, 5A, 50W
98	2SK1117	N-Channel	600V, 6A, 100W
99	2SK1118	N-Channel	600V, 6A, 45W
100	2SK1507	N-Channel	600V, 9A, 50W, 1ohm
101	2SK1531	N-Channel	500V, 15A, 150W, 0.45ohm
102	2SK1794	N-Channel	900V, 6A, 100W, 2.8ohm
103	2SK2038	N-Channel	800V, 5A, 125W, 2.2ohm
104	2SK2039	N-Channel	900V, 5A, 150W, 2.5ohm
105	2SK2134	N-Channel	200V, 13A, 70W, 0.4ohm
106	2SK2136	N-Channel	200V, 20A, 75W, 0.18ohm
107	2SK2141	N-Channel	600V, 6A, 35W, 1.1ohm
108	2SK2161	N-Channel	200V, 9A, 25W, 0.35ohm